

## CREATE II 1 LIGHT SUSPENSION CORD

SKU# 011444,011445, 011446, 011447, 011448, 011458 ,011459

Rated Voltage 220-240V~ 50Hz.

**NOTE:** This instruction manual is the installation directions for the luminaire only.

The shade is sold separately, refer to the instruction manual included with the shade for installation directions.

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 12-month warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

### Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules. E.g., AS/NZS 3000 Electrical Installations.
- This luminaire is a Class I product and must be earthed during wiring and installation.
- Do not exceed the maximum wattage rating.
- Select a suitable location for installation:
  - This luminaire is suitable for indoor use only.
  - The mounting point must support 2 times the weight of the fitting.
  - Ensure the luminaire is not installed in direct line of an air vent/system.
  - If installing a luminaire in an area prone to moisture, ensure that the area is well ventilated, and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

## Installation Directions

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material. If assembly is required, place the luminaire on a smooth non-scratch surface.
2. Determine the suspension length required for your installation location. If the length of the suspension cord (K), requires adjustment, loosen the cord anchorage (H) and adjust the length of the suspension cord (K). Tighten the cord anchorage (H), take care not to overtighten and damage the cord.
3. Remove the mounting bracket (B) from the canopy (F) by loosening the screws (C) on the sides.
4. Use the mounting bracket (B) as a template to mark the screw hole positions on the ceiling.
5. Install the mounting bracket (B) onto the ceiling by using appropriately sized mounting screws (D) and anchors (A). Ensure the screws (D) and anchors (A) used are suitable for the mounting surface and the surrounding environment.
6. Connect the mains supply wire to the terminal block (E).

### Mains Supply Wire

Earth – Yellow/Green

Neutral – Blue or Black

Live – Brown or Red

### Luminaire Wire / Terminal block

Yellow/Green or 

Blue or N

Brown or L

7. Ensure the wires are secure, and no bare wires are exposed.

**NOTE: The luminaire is a Class I product and must be earthed during wiring and installation.**

8. Install the canopy (F) onto the mounting bracket (B) and secure by tightening the screws (C) on the sides.

**NOTE: If you have bought a finishing kit (J- Canopy Cover, L- Lamp Holder Cover & N- Lamp Shade ring, sold separately), refer to the instruction manual included with the finishing kit for installation directions.**

9. Install a globe (O - not included) into the lamp holder (M). Do not exceed the maximum wattage rating.
10. After the installation, switch on the luminaire to test and enjoy your new lighting product.

**NOTE: A compatible shade is sold separately, refer to the instruction manual included with the shade for installation directions.**

**NOTE: Check and confirm the maximum allowable weight of the shade to be used with each model pendant in the specifications table on the last page.**

**Ensure the weight of the shade does not exceed the amount specified.**



Specifications							
<b>SKU #</b>	011444	011445	011446	011447	011448	011458	011459
<b>Colour</b>	Black	Tan	Off White	Grey	Natural	Black	Off White
<b>Rated Voltage</b>	220-240V~ 50Hz						
<b>Rated Wattage</b>	45W Max.						
<b>Lamp Holder</b>	ES / E27						
<b>Luminaire Weight</b>	Total 0.6kg (Suspension kit + Finishing Kit only)					Total 0.7kg (Suspension kit + Finishing Kit only)	
<b>Maximum weight of shade</b>	1.5kg						
<b>Canopy Dimensions</b>	H:20mm Dia:90mm						
<b>Luminaire Dimensions</b>	H:95mm Dia:45mm Susp:1500mm (with Create II Finishing Kit installed – sold separately)					H:95mm Dia:45mm Susp:3000mm (with Create II Finishing Kit installed – sold separately)	