

## LEXICON 3 LIGHT BAR PENDANT

SKU# 011702, 011703

Rated Voltage 220-240V~ 50Hz

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 12-month warranty. The warranty is from the date of purchase not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

### Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules. E.g. AS/NZS 3000 Electrical Installations.
- The luminaire is a Class I product and must be earthed during wiring and installation.
- Do not exceed the maximum wattage rating.
- Select a suitable location for installation:
  - This luminaire is suitable for indoor use only.
  - The mounting point must support 2 times the weight of the luminaire.
  - If installing a luminaire in an area prone to moisture, ensure that the area is well ventilated, and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

## Installation Directions

**NOTE: Assembly and installation of this luminaire must be done by a licensed electrician.**

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material. If assembly is required, place the luminaire on a smooth non-scratch surface.
2. Remove the mounting bracket (B) from the canopy (E) by loosening the nuts (G) on the bottom.
3. Determine the suspension length required for your installation location. If the length of the suspension cord (H), requires adjustment, loosen the cord anchorage (F) and adjust the length of the suspension cord (H). Tighten the cord anchorage (F), take care not to overtighten and damage the cord.
4. Use the mounting bracket (B) as a template to mark the screw hole positions on the ceiling.
5. Install the mounting bracket (B) onto the ceiling by using appropriately sized mounting screws (C) and anchors (A). Ensure the screws (C) and anchors (A) used are suitable for the mounting surface and the surrounding environment.
6. Connect the mains supply wires to the terminal block (D). Ensure the wires are secure and no bare wires are exposed.

### Mains Supply Wire

Earth – Yellow/Green

Neutral – Blue or Black

Live – Brown or Red

### Luminaire Wire / Terminal Block

Yellow/Green or 

Blue or N

Brown or L

**NOTE: This luminaire is a Class I product and must be earthed during wiring and installation.**

**NOTE: Ensure the earth wire from the mounting bracket (B) and the earth wire from the luminaire Canopy (E) are both connected to the terminal block (D).**

7. Install the canopy (E) onto the mounting bracket (B) and secure by tightening the nuts (G) on the bottom.
8. Install the decorative ring (**K - sold separately SKU# 011676, 011677, 011678, 011679, 011699**) followed by the shade (L) on the main body (I), then secure by the lamp holder ring (M). (Figure 1)  
Alternatively, Install the shade (L) on the main body (I) securing by the lamp holder ring (M) and the decorative ring (O). (Figure 2)

**NOTE: This luminaire is only compatible with the following shades (sold separately): SKU# 011630,011631, 011632,011633,011634,011653,011654,011655,011656,011657,011658,011668,011669,011674,011675,011686,011687,011688,011692,011693,011694,011695,011696,011697.**

9. Install globes (N – not included) into the lamp holders (J). Do not exceed the maximum wattage rating.
10. After the installation, switch on the fitting to test and enjoy your new lighting product.




Figure 1




Figure 2

## Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globes or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- Select a suitable location away from liquids and hazards.
- To clean wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.

## Specifications

SKU #	011702	011703
Colour	Black	White
Rated Voltage	220-240V~ 50Hz	
Rated Wattage	84W Max. (3 x Max. 28W)	
Lamp Holder	ES / E27	
Weight	2.1kg (without shade) 6.2kg (Max. weight with shade)	
Canopy Dimensions	L:460mm W:60mm H:25mm	
Luminaire Dimensions	H:165mm L:1100mm W:100MM Susp:2000mm MAX (without shade)	