

## CALLEA 1 LIGHT LED PENDANT

SKU# 028229

Rated Voltage 220-240V~ 50Hz

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this luminaire. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 3-year warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- This luminaire is not suitable for use with dimmer switches. The warranty will be void if this luminaire is used on the same circuit which has a dimmer switch.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

### Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules. e.g. AS/NZS 3000 Electrical Installations.
- This luminaire is a Class II product and must be maintained during wiring and installation.

**NOTE: Cables or wires of different voltage systems (e.g. Low Voltage and SELV), must be separated by double insulation.**

**NOTE: Ensure the mains supply wire connection to the terminal block is double insulated.**

- Select a suitable location for installation:
  - This luminaire is suitable for indoor use only.
  - The mounting point must support 2 times the weight of the luminaire.
  - If installing a luminaire in an area prone to moisture, ensure that the area is well ventilated, and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- This luminaire is not suitable for use with dimmer switches. The warranty will be void if this luminaire is used on the same circuit which has a dimmer switch.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.

## Installation Directions

**WARNING: Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.**

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material. If assembly is required, place the luminaire on a smooth non-scratch surface.
2. Remove the mounting bracket from the canopy by loosening the screws on the side. (Fig. B)
3. Use the mounting bracket as a template to mark the screw hole positions on the ceiling. (Fig. A)
4. Install the mounting bracket onto the ceiling by using appropriately sized mounting screws and anchors. (Fig. A)  
Ensure the screws and anchors used are suitable for the mounting surface and the surrounding environment.
5. Determine the suspension length required for your luminaire at the installation location:
  - If the cord suspension needs to be reduced – The excess cord can be pulled through the cord anchorage and into the canopy until the desired length has been reached.
  - If the cord suspension needs to be extended (maximum length 1660mm) – Press in and hold the middle cylinder of the cord anchorage and pull the suspension cord back out of the canopy.
6. Open the terminal box and connect the mains supply wire to the terminal block. (Fig. B)

**Mains Supply Wire**

Neutral – Blue or Black

Live – Brown or Red

**Luminaire Wire / Terminal Block**

Blue or N


Brown or L

**NOTE: This luminaire is a Class II product and must be maintained during wiring and installation.**

**NOTE: Cables or wires of different voltage systems (e.g. Low Voltage and SELV), must be separated by double insulation.**

**NOTE: Ensure the mains supply wire connection to the terminal block is double insulated.**

7. Ensure the wires are secure and no bare wires are exposed.
8. Install the cover back over the terminal box.
9. Install the canopy onto the mounting bracket and secure by tightening the screws on the sides. (Fig. B)
10. After the installation is complete, switch on the luminaire to test and enjoy your new lighting product. (Fig. C)



## Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- Select a suitable location away from liquids and hazards.
- To clean, wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.
- The light source of this luminaire is not replaceable; when the light source reaches its end of life, the whole luminaire shall be replaced. There are no serviceable parts, do not attempt to dismantle or open the product.

## Specifications

|                      |  |
|----------------------|--|
| SKU #                | 028229   |
| Rated Voltage        | 220-240V~ 50Hz                                     |
| Rated Wattage        | 6W   |
| LED Specs            | 300 lumens, Warm White 3000K, Non-Dimmable, CRI≥80 |
| Weight               | 1.1kg  |
| Canopy Dimensions    | H:35mm Dia:140mm                                   |
| Luminaire Dimensions | H:105mm Dia:110mm Susp:1660mm MAX                  |