

## SANTORINI CLOSE TO CEILING

SKU# 239650

Rated Voltage 220-240V~ 50Hz

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this luminaire. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 5-year warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

### Installation Requirements

- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules.  
e.g. AS/NZS 3000 Electrical Installations.
- The luminaire is a Class I product and must be earthed during wiring and installation.
- This luminaire is rated IP64 and must be maintained during wiring and installation.
- Do not exceed the maximum wattage rating.
- This luminaire must be used with a LED lamp only.
- Select a suitable location for installation:
  - This luminaire is suitable for indoor or outdoor use.
  - The mounting point must support 2 times the weight of the luminaire.
  - This luminaire is rated against water penetration to IP64 standards, which is water splashing from any direction.
- If the diffuser is cracked or damaged. For your safety, discontinue use and replace the diffuser before using the luminaire again.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.



Installation Directions

**WARNING: Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.**

- 1. Remove the diffuser, washer and cage by twisting is off from the luminaire.
- 2. Use the luminaire as a template to mark the 2 screw hole positions on the mounting surface.
- 3. Drill the 2 installation holes onto the mounting surface.
- 4. Feed the mains supply wire through the luminaire.
- 5. Install the luminaire onto the mounting surface by using 2 appropriately sized mounting screws and anchors.  
Ensure the 2 screws and anchors used are suitable for the mounting surface and the surrounding environment.


**NOTE: A non-corrosive bead of silicon MUST be applied before installation onto the mounting surface, ensuring that no water can run down into the cabling and enter the luminaire.**

- 6. Connect the mains supply wire to the earthing point on the luminaire body and the E27/ES lamp holder.

**Mains Supply Wire**

Earth – Yellow/Green

**Luminaire Body**

 Earthing point on the luminaire

**Mains Supply Wire**

Neutral – Blue or Black

**E27/ES Lamp Holder Terminals**


N (side pin)

Live – Brown or Red

L (centre pin)



**NOTE: The E27/ES lamp holder terminals are not suited for loose strands or bare wires.**



**NOTE: Ensure the wire ends are crimped and there are no loose strands or bare wires.**

**NOTE: Check & ensure the correct polarity for the E27/ES lamp holder. Live for centre pin. Neutral for side pin.**

**NOTE: This luminaire is a Class I product and must be earthed during wiring and installation.**

- 7. Ensure the wires are secure and no bare wires are exposed.
- 8. Install the lamp holder onto the luminaire and secure using the 2 screws.
- 9. Install a LED lamp (not included) into the lamp holder. Do not exceed the maximum wattage rating.
- 10. Install the diffuser, washer and cage, by twisting and securing it back onto the luminaire.
- 11. After the installation is complete, switch on the luminaire to test and enjoy your new lighting product.

Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning or changing the lamp.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- To clean, wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.
- If the diffuser is cracked or damaged. For your safety, discontinue use and replace the diffuser before using the luminaire again.

Specifications

SKU #	239650
Rated Voltage	220-240V~ 50Hz
Rated Wattage	15W Max. (LED lamp only)
Protection Class	Class I
Lamp Holder	E27 / ES
IP Rating	IP64
Weight	0.9kg
Dimensions	H:190mm Dia:130mm