

## TRAVIATO 2 LIGHT UP/DOWN WALL BRACKET

SKU# 307011, 307012

Rated Voltage 220-240V~ 50Hz

To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 12-month warranty. The warranty is from the date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician, the warranty will be void.
- Please retain the proof of purchase and evidence of installation by a licensed electrician for any warranty enquiries.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void the warranty.

### Installation Requirements


- This luminaire must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to the latest local and national wiring rules.  
E.g. AS/NZS 3000 Electrical Installations.
- This luminaire is a Class I product and must be earthed during wiring and installation.
- Do not exceed the maximum wattage rating. This luminaire must be used with LED lamps only.
- Select a suitable location for installation:
  - This luminaire is suitable for indoor use only.
  - The mounting point must support 2 times the weight of the luminaire.
  - If installing a luminaire in an area prone to moisture, ensure that the area is well ventilated, and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure no components are missing before assembling.
- If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

Installation Directions

- 1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material. If assembly is required, place the luminaire on a smooth non-scratch surface.
- 2. Use the luminaire body (B) as a template to mark the screw positions on the wall.
- 3. Use a Phillips head screwdriver to loosen the screw (D) on the cord anchorage (E) for the mains supply wire end of the terminal box. open the cover (F) of the terminal box.
- 4. Prepare the mains supply wire to make a connection to the terminal block.

**NOTE: The bare wire must be no more than 8mm in length.**  
**NOTE: For the remaining mains supply wire basic insulation, use the heat shrink tube provided to ensure double insulation is achieved.**

- 5. Connect the mains supply wire to the terminal block (G). Ensure the wires are secure, and no bare wires are exposed.


Mains Supply Wire	Luminaire Wire / Terminal block
Earth – Yellow/Green	Yellow/Green or 
Neutral – Blue or Black	Blue or N
Live – Brown or Red	Brown or L

**NOTE: THE INSTALLING ELECTRICIAN MUST ENSURE THE SUPPLY WIRE MAINTAINS DOUBLE INSULATION AFTER CONNECTING TO THE TERMINAL BLOCK.**

- 6. Place the mains supply wire into the cord anchorage (E) and secure by tightening the screw (D) with a Phillips head screwdriver.
- 7. Reinstall the cover (F) back onto the terminal box and ensure it is secure by clicking the cover into the tabs.

**CAUTION: CHECK AND ENSURE ALL ACTIVE WIRES ON THE MAINS SUPPLY SIDE ARE NOW DOUBLE INSULATED**

- 8. Install the luminaire body (B) onto the wall by using appropriately sized mounting screws (C) and anchors (A). Ensure the screws (C) and anchors (A) used are suitable for the mounting surface and the surrounding environment.
- 9. Pull both the lamp holders (K) to the ends of the shade (J) so they can be easily accessible to install the globes.
- 10. Hang the shade (J) onto the luminaire body (B).
- 11. Install globes (I, not included) into the lamp holders (K) and secure the globes onto the shade by using the spring clips (H). Do not exceed the maximum wattage rating, and ensure globes used do not exceed maximum allowable globe height of 56mm.
- 12. After the installation, switch on the luminaire to test and enjoy your new lighting product.



Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globe or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- Select a suitable location away from liquids and hazards.
- To clean, wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.

Specifications

SKU #	307011	307012
Colour	Travertine	Lava Stone
Rated Voltage	220-240V~ 50Hz	
Rated Wattage	16W Max. (2x Max. 8W LED globes only)*	
Lamp Holder	GU10	
Weight	2.8kg	
Luminaire Dimensions	H:220mm W:175mm E:85mm	

\* Globe height: 56mm MAX