

## EMPIRE LARGE CHANDELIER

SKU# 050621

Rated Voltage 220-240V~ 50Hz

Thank you for purchasing this quality Lucci product. To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this product. Please keep instructions for future reference.

### Warranty

- This luminaire is covered by a 12 month warranty. The warranty is from date of purchase, not the date of installation.
- If the luminaire is not assembled and installed by a licensed electrician the warranty will be void.
- Please retain proof of purchase and evidence of installation by a licensed electrician.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void warranty.

### Installation requirements

- Must be assembled and installed by a licensed electrician.
- All wiring and installation of the luminaire must adhere to latest local and national wiring rules.  
Eg. AS/NZS 3000:2007/Amendment 2:2012 Electrical installations.
- Do not exceed the maximum wattage rating.
- Select a suitable location for installation:
  - This product is suitable for indoor use only.
  - The mounting point must support 2 times the weight of the luminaire.
  - Ensure the luminaire is not installed in direct line of an air vent/system.
  - If installing a luminaire in an area prone to moisture, ensure that the area is well ventilated and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure there are no components missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any product which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Ensure power to the circuit you are working on has been switched OFF before commencing any electrical work.

### Installation directions

**NOTE: Due to the size of the luminaire, two people may be required to lift up the luminaire during installation.**

1. Remove all packaging material from the product and be careful not to throw away accessories that may be hidden within the packaging material.
2. Use the mounting bracket (B) as a template to mark the screw positions on the ceiling.
3. Install the mounting bracket (B) onto the ceiling by using appropriately sized mounting screws (C) and anchors (A). Ensure the screws (C) and anchors (A) used are suitable for the mounting surface and the surrounding environment.
4. Loop the safety loading wire (L) onto the mounting bracket (B). Fix the loading wire (L) by tightening the screw (D).
5. Determine the suspension length required for your installation location and install the chain (J) onto the ring of the main body.

The chain suspension length can be adjusted by using the chain link connectors (G).

**NOTE: Check and ensure the load/weight of the fitting is NOT on the supply cord (K) or the safety loading wire (L). The full load/weight of the pendant must always be on the chain suspension.**

# Installation Instructions

6. Use the ring (F) to hang the luminaire up onto the mounting bracket (B).
7. Connect the mains supply wire to the terminal block (E). Ensure the wires are secure and no bare wires are exposed.

## Mains Supply Wire

Earth – Yellow/Green

Neutral – Blue or Black

Live – Brown or Red


## Luminaire Wire

Yellow/Green or 

Blue or N

Brown or L

8. Push the canopy (H) up to cover the mounting bracket (B) and secure by tightening the screw (I).
9. Install globes (N - not included) into the lamp holders. Do not exceed the maximum wattage rating.
10. Install the decorative drops (O & P) to the luminaire accordingly.
11. After the installation, switch on the luminaire to test and enjoy your new lighting product.



## Safety tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globe or making any adjustment to the luminaire.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- Select a suitable location away from liquids and hazards.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.
- To clean, wipe with a damp clean cloth. Do NOT soak or immerse the product in water or other liquids.

## Specifications

SKU #	050621
Colour	Black
Rated Voltage	220-240V~ 50Hz
Rated Wattage	540W Max. (12 x Max.45W)
Lamp Holder	SES / E14
Weight	15kg
Canopy size	H:85mm Dia:120mm
Dimensions	H:650mm Dia:580mm Susp:2000mm