

COPENHAGEN FLOOR LAMP

SKU#280074, 280084

Rated Voltage 220-240V~ 50Hz

Thank you for purchasing this quality Lucci product. To ensure correct function and safety, please read and follow all instructions carefully before assembly, installation and use of this luminaire. Please keep the instructions for future reference.

Warranty


- This luminaire is covered by a 12 month warranty from the date of purchase. Please retain proof of purchase.
- Warranty will be void if there is any damage due to improper usage or modification to the luminaire.
- Failure to comply with the instructions in this manual may increase the risk of damage or injury and will void warranty.

Installation Requirements

- Select a suitable location for this luminaire:
 - Ensure it is on a flat and stable surface.
 - This luminaire is suitable for indoor use only.
 - Do not place flammable material near or over the luminaire.
 - Ensure the luminaire is not installed in direct line of an air vent/system.
 - If the luminaire is placed in an area prone to moisture, ensure that the area is well ventilated and an appropriately rated exhaust fan is used if required. Damage or corrosion caused by moisture is not a product fault, and as such is not covered under warranty.
- Do not exceed the maximum wattage rating.
- Take care not to pull any electrical wires during unpacking as this may damage the connection.
- Lay out all the components on a smooth surface and make sure there are no components missing before assembling. If parts are missing, return the complete product to the place of purchase for inspection or replacement.
- Check whether the luminaire has been damaged during transport. Do not operate/install any luminaire which appears damaged in any way. Return the complete product to the place of purchase for inspection, repair or replacement.
- Do not plug into the mains power socket outlet before or during assembly. Only do so after the luminaire is fully assembled with the globe installed and is ready to use for the first time.

Installation Directions

1. Remove all packaging material from the luminaire and fabric lamp shade (B).
2. Place the product on a non-scratch surface to help with assembly.
3. Install the lamp holder (D) onto the body (E). Carefully pull the cord out from the bottom and twist as you go to remove any slack or twist in the cord during installation. Take care not to damage the cord during assembly.
4. Remove the lamp holder skirt (A) from the lamp holder (D).
5. Install the fabric lamp shade (B) onto the lamp holder (D) and secure using the lamp holder skirt (A).
6. Install a globe (C - not included) into the lamp holder (D). Do not exceed the maximum rated wattage.
7. Select a suitable location for the luminaire. See the installation requirements above.
8. Insert the plug (G) into the mains power socket outlet and ensure it is fully plugged in.
9. Turn power on at the mains power socket outlet.
10. Use the cord line switch (F) to turn the luminaire on/off.



NOTE: Wood is a natural material. Some variations in its appearance may occur which is normal and part of its design quality.

Safety Tips

- Always ensure the power is OFF and the luminaire has cooled down before performing any maintenance, cleaning, changing the globe or making any adjustment to the luminaire.
- The external flexible cable or cord of this luminaire cannot be replaced; if the cable or cord is damaged, the luminaire shall be destroyed.
- To avoid injury or damage to the luminaire, ensure that power leads and screws are secure before connecting the power.
- Young children should be supervised to ensure that they do not play with the portable lamp.
- Handle the luminaire and/or shade with care to avoid any damage or breakage.
- Select a suitable location away from liquids and hazards.
- To clean, wipe with a soft damp cloth. Do NOT soak or immerse the luminaire in water or other liquids.
- Ensure that the luminaire does not come in contact with corrosive chemicals/solvents or abrasive cleaners etc.

Specifications

SKU #	280074	280084
Colour	Natural	Black
Rated Voltage	220-240V~ 50Hz	
Rated Wattage	100W Max.	
Lamp Holder	ES / E27	
Weight	5.6kg	
Dimensions	H:1680mm Dia:510mm	